


SOS-01

尺寸: L50*H60mm (折页)

材质: 80g 双铜

印刷: 彩色

offgridtec
SOS
Emergency call button
Instructions



Appearance Introduction

SOS button, Light, USB charging, Lanyard

Preparation before connecting to the APP

Download APP
Smart Life

Scan the QR code to download.
Please search for "Smart Life" in the application market to download.

Configuration network considerations

Wi-Fi : 2.4GHz IEEE 802.11 b/g/n
≤ 15 meters (open/undisturbed)

Warm prompt
The distances varies with the environment.
If the button is too far from the router, it will not be able to connect to the phone.

Connect to mobile app

Connect your phone to WiFi (2.4G) and turn on Bluetooth.

Enter the configuration network state.

Press and hold the button for 5 seconds, and the LED indicator light Flashing rapidly .

Warm prompt
The duration of configuring network status is 2 minutes.

Open the APP and click "Add Device".

After automatically discovering the device, click "Add".

Enter WiFi information and password.

Waiting for successful connection.

Successfully connected, click "Done".

Alarm push notification

Short press
The LED indicator flashes quickly.

Multi-person sharing

Click on the upper right corner

Click "Share Device".

Click "Add Sharing".

Choose a sharing method.

Installation

Installation method:

Double-sided tape can stick SOS button to the bathroom / toilet / kitchen, etc.

Lanyard design that can be hung around the neck.

Double sided adhesive installation

Tear off one side of the double-side adhesive tape.

Paste on the back of the button.

Q&A

Q: After configuring the network, trigger the button. The LED indicator light is constantly flashing.
A: (1) Because the button has exceeded the WiFi range, the alarm is not successfully reported. Need to approach Wi-Fi and stop flashing after successful reporting.
(2) automatically stop after Waiting for 2 minutes.

Q: Unable to connect to mobile app?
A: The button is too far away from the router, please connect within 1-3 meters of the router.

Technical Specifications:

Standby current: ≤ 20uA
Average current: ≤ 85mA
Internal battery: Polymer battery 3.7V/400mAh
Charging duration: ≤ 1 hour
Wi-Fi: 2.4GHz IEEE 802.11 b/g/n

Offgridtec AG
Im Gewerbepark 11
84307 Eggenfelden
Germany